

**3rd Generation Partnership Project;  
Technical Specification Group Radio Access Network;  
3GPP TS 38.508-2 V16.1.0 (2019-09)  
5GSA**

**User Equipment (UE) conformance specification;  
Part 2: Common Implementation Conformance Statement (ICS)  
proforma (Release 16)**



The present document has been developed within the 3rd Generation Partnership Project (3GPP™) and may be further elaborated for the purposes of 3GPP..  
The present document has not been subject to any approval process by the 3GPP Organizational Partners and shall not be implemented.  
This Specification is provided for future development work within 3GPP only. The Organizational Partners accept no liability for any use of this Specification.

Specifications and Reports for implementation of the 3GPP™ system should be obtained via the 3GPP Organizational Partners' Publications Offices.

---

Keywords  
5GS, UE, terminal, testing

---

**3GPP**

Postal address

3GPP support office address

650 Route des Lucioles - Sophia Antipolis  
Valbonne - FRANCE  
Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Internet

<http://www.3gpp.org>

***Copyright Notification***

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© 2019, 3GPP Organizational Partners (ARIB, ATIS, CCSA, ETSI, TSDSI, TTA, TTC).  
All rights reserved.

UMTS™ is a Trade Mark of ETSI registered for the benefit of its members  
3GPP™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners  
LTE™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners  
GSM® and the GSM logo are registered and owned by the GSM Association

---

---

# Contents

Foreword.....	5
1 Scope.....	6
2 References.....	6
3 Definitions, symbols and abbreviations.....	8
3.1 Definitions.....	8
3.2 Symbols.....	8
3.3 Abbreviations.....	8
<b>Annex A (normative):ICS proforma for NR/5GS Generation User Equipment.....</b>	<b>9</b>
A.1 Guidance for completing the ICS proforma.....	9
A.1.1 Purposes and structure.....	9
A.1.2 Abbreviations and conventions.....	9
A.1.3 Instructions for completing the ICS proforma.....	10
A.2 Identification of the User Equipment.....	10
A.2.1 Date of the statement.....	10
A.2.2 User Equipment Under Test (UEUT) identification.....	10
A.2.3 Product supplier.....	11
A.2.4 Client.....	11
A.2.5 ICS contact person.....	12
A.3 Identification of the protocol.....	12
A.4 ICS proforma tables.....	12
A.4.1 UE Implementation Types.....	12
A.4.2 UE Service Capabilities.....	14
A.4.2.1 3GPP Standardised UE Service Capabilities.....	14
A.4.2.1.1 Bearer Services.....	14
A.4.3 Baseline Implementation Capabilities.....	14
A.4.3.1 RF Baseline Implementation Capabilities.....	14
A.4.3.2 Physical Layer Baseline Implementation Capabilities.....	17
A.4.3.2A NR CA Physical Layer Baseline Implementation Capabilities.....	18
A.4.3.2A.1 General NR CA capabilities.....	18
A.4.3.2A.2 NR CA Intra-band contiguous.....	19
A.4.3.2A.2.1 NR CA Intra-band contiguous with FR1.....	19
A.4.3.2A.2.2 NR CA Intra-band contiguous with FR2.....	21
A.4.3.2A.3 NR CA Intra-band non-contiguous.....	23
A.4.3.2A.3.1 NR CA Intra-band non-contiguous with FR1.....	23
A.4.3.2A.3.2 NR CA Intra-band non-contiguous with FR2.....	23
A.4.3.2A.4 NR Inter-band CA.....	24
A.4.3.2A.4.1 NR Inter-band CA with FR1 (two bands).....	24
A.4.3.2B NR DC Physical Layer Baseline Implementation Capabilities.....	25
A.4.3.2B.1 NR DC between FR1 and FR2.....	25
A.4.3.2B.2 EN-DC Physical Layer Baseline Implementation Capabilities.....	26
A.4.3.2B.2.1 EN-DC Intra-band contiguous with NR FR1.....	26
A.4.3.2B.2.2 EN-DC Intra-band non-contiguous with FR1.....	26
A.4.3.2B.2.3 EN-DC Inter-band.....	26
A.4.3.2B.2.3.1 EN-DC Inter-band with FR1 (two bands).....	26
A.4.3.2B.2.3.2 EN-DC Inter-band with FR1 (three bands).....	27
A.4.3.2B.2.3.3 EN-DC Inter-band with FR1 (four bands).....	27
A.4.3.2B.2.3.4 EN-DC Inter-band with FR1 (five bands).....	28
A.4.3.2B.2.3.5 EN-DC Inter-band with FR1 (six bands).....	28
A.4.3.2B.2.3.6 EN-DC Inter-band with FR2 (two bands).....	28
A.4.3.2B.2.3.7 EN-DC Inter-band with FR2 or with both FR1 and FR2 (three bands).....	28
A.4.3.2B.2.3.8 EN-DC Inter-band with FR2 or with both FR1 and FR2 (four bands).....	28
A.4.3.2B.2.3.9 EN-DC Inter-band with FR2 or with both FR1 and FR2 (five bands).....	29

A.4.3.2B.2.3.10	EN-DC Inter-band with FR2 or with both FR1 and FR2 (six bands).....	29
A.4.3.3	PDCP Implementation Capabilities.....	29
A.4.3.4	RLC Implementation Capabilities.....	29
A.4.3.5	MAC Implementation Capabilities.....	30
A.4.3.6	Measurement Capabilities.....	30
A.4.3.7	General Capabilities.....	31
A.4.3.8	Mobility Capabilities.....	31
A.4.4	Additional information.....	33
Annex B (informative):	Change history.....	35

---

## Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

The present document is part 2 of a multi-part deliverable covering the 5G System (5GS) User Equipment (UE) protocol conformance specification, as identified below:

- 3GPP TS 38.508-1 [11]: "5GS; User Equipment (UE) conformance specification; Part 1: Common test environment".
- 3GPP TS 38.508-2: "**5GS; User Equipment (UE) conformance specification; Part 2: Common Implementation Conformance Statement (ICS) proforma**" (the present document).

---

## 1 Scope

The present document provides the Implementation Conformance Statement (ICS) proforma for 5G New Radio (NR) User Equipment (UE), in compliance with the relevant requirements.

Special conformance testing functions can be found in 3GPP TS 38.509 [12] and 3GPP TS 36.509 [14] and the common test environments are included in 3GPP TS 38.508-1 [11] and 3GPP TS 36.508 [13].

The present document is valid for UE implemented according to 3GPP Releases starting from Release 15 up to the Release indicated on the cover page of the present document.

---

## 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 38.523-1: "5GS; UE conformance specification; Part 1: Protocol conformance specification".
- [3] 3GPP TS 38.523-2: "5GS; User Equipment (UE) conformance specification; Part 2: Applicability of protocol test cases".
- [4] 3GPP TS 38.523-3: "5GS; User Equipment (UE) conformance specification; Part 3: Protocol Test Suites".
- [5] 3GPP TS 38.521-1: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Range 1 Standalone".
- [6] 3GPP TS 38.521-2: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 2: Range 2 Standalone".
- [7] 3GPP TS 38.521-3: "NR; User Equipment (UE) conformance specification; Radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios".
- [8] 3GPP TS 38.521-4: "NR; User Equipment conformance specification; Radio transmission and reception; Part 4: Performance".
- [9] 3GPP TS 38.522: "NR; User Equipment (UE) conformance specification; Applicability of radio transmission, radio reception and radio resource management test cases".
- [10] 3GPP TS 38.523: "NR; User Equipment (UE) conformance specification; Radio resource management".
- [11] 3GPP TS 38.508-1: "5GS; User Equipment (UE) conformance specification; Part 1: Common test environment".
- [12] 3GPP TS 38.509: "5GS; Special conformance testing functions for UE".
- [13] 3GPP TS 36.508: "Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Universal Terrestrial Radio Access (E-UTRAN); Common Test Environments for User Equipment (UE) Conformance Testing".

- [14] 3GPP TS 36.509: "Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Universal Terrestrial Radio Access Network (E-UTRAN); Special conformance testing functions for User Equipment (UE)".
- [15] 3GPP TS 34.229-2: "Internet Protocol (IP) multimedia call control protocol based on Session Initiation Protocol (SIP) and Session Description Protocol (SDP);User Equipment (UE) conformance specification; Part 2: Implementation Conformance Statement (ICS) specification".
- [16] 3GPP TS 36.523-2: "Evolved Universal Terrestrial Radio Access (E-UTRA) and Evolved Universal Terrestrial Radio Access (E-UTRAN); User Equipment (UE) conformance specification; Part 2: Implementation Conformance Statement (ICS) proforma specification".
- [17] 3GPP TS 38.306: "NR; User Equipment (UE) radio access capabilities".
- [18] ISO/IEC 9646-7: "Information technology - Open systems interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".
- [19] 3GPP TS 38.307: "NR; User Equipments (UEs) supporting a release-independent frequency band".
- [20] 3GPP TS 37.340:"Evolved Universal Terrestrial Radio Access (E-UTRA) and NR; Multi-connectivity; Stage 2".
- [21] 3GPP TS 38.300: "NR; NR and NG-RAN Overall Description; Stage 2".
- [22] 3GPP TS 24.229: "IP multimedia call control protocol based on Session Initiation Protocol (SIP) and Session Description Protocol (SDP); Stage 3"
- [23] 3GPP TS 38.101-1: "NR; User Equipment (UE) radio transmission and reception; Part 1: Range 1 Standalone"
- [24] 3GPP TS 38.101-2: "NR; User Equipment (UE) radio transmission and reception; Part 2: Range 2 Standalone"
- [25] 3GPP TS 38.101-3: "NR; User Equipment (UE) radio transmission and reception; Part 3: Range 1 and Range 2 Interworking operation with other radios"

---

## 3 Definitions, symbols and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [5] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [5].

**Implementation Conformance Statement (ICS):** statement made by the supplier of an implementation or system claimed to conform to a given specification, stating which capabilities have been implemented

**ICS proforma:** document, in the form of a questionnaire, which when completed for an implementation or system becomes an ICS

**Implementation extra Information for Testing (IXIT):** A statement made by a supplier or implementer of an UEUT which contains or references all of the information (in addition to that given in the ICS) related to the UEUT and its testing environment, which will enable the test laboratory to run an appropriate test suite against the UEUT

**IXIT proforma:** A document, in the form of a questionnaire, which when completed for an UEUT becomes an IXIT

**Protocol Implementation Conformance Statement (PICS):** An ICS for an implementation or system claimed to conform to a given protocol specification

**Protocol Implementation extra Information for Testing (PIXIT):** An IXIT related to testing for conformance to a given protocol specification

**Static conformance review:** A review of the extent to which the static conformance requirements are claimed to be supported by the UEUT, by comparing the answers in the ICS(s) with the static conformance requirements expressed in the relevant specification(s)

### 3.2 Symbols

For the purposes of the present document, the following symbols apply:

<symbol>      <Explanation>

### 3.3 Abbreviations

For the purposes of the present document, the abbreviations given in 3GPP TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in 3GPP TR 21.905 [1].

For the purposes of the present document, the following abbreviations apply:

FFS	For Further Study
ICS	Implementation Conformance Statement
IXIT	Implementation extra Information for Testing
PICS	Protocol Implementation Conformance Statement
PIXIT	Protocol Implementation extra Information for Testing
SCS	System Conformance Statement
TC	Test Case
UEUT	User Equipment Under Test

---

# Annex A (normative): ICS proforma for NR/5GS Generation User Equipment

Notwithstanding the provisions of the copyright clause related to the text of the present document, The Organizational Partners of 3GPP grant that users of the present document may freely reproduce the ICS proforma in this annex so that it can be used for its intended purposes and may further publish the completed ICS.

---

## A.1 Guidance for completing the ICS proforma

### A.1.1 Purposes and structure

The purpose of this ICS proforma is to provide a mechanism whereby a supplier of an implementation of the requirements defined in relevant specifications may provide information about the implementation in a standardised manner.

The ICS proforma is subdivided into clauses for the following categories of information:

- instructions for completing the ICS proforma;
- identification of the implementation;
- identification of the protocol;
- ICS proforma tables (for example: UE implementation types, Teleservices, etc).

### A.1.2 Abbreviations and conventions

The ICS proforma contained in this annex is comprised of information in tabular form in accordance with the guidelines presented in ISO/IEC 9646-7 [18].

#### Item column

The item column contains a number which identifies the item in the table.

#### Item description column

The item description column describes in free text each respective item (e.g. parameters, timers, etc.). It implicitly means "is <item description> supported by the implementation?".

#### Reference column

The reference column gives reference to the relevant 3GPP core specifications.

#### Release column

The release column indicates the earliest release from which the capability or option is relevant.

#### Mnemonic column

The Mnemonic column contains mnemonic identifiers for each item.

#### Comments column

This column is left blank for particular use by the reader of the present document.

## References to items

For each possible item answer (answer in the support column) within the ICS proforma there exists a unique reference, used, for example, in the conditional expressions. It is defined as the table identifier, followed by a solidus character "/", followed by the item number in the table. If there is more than one support column in a table, the columns shall be discriminated by letters (a, b, etc.), respectively.

### A.1.3 Instructions for completing the ICS proforma

The supplier of the implementation may complete the ICS proforma in each of the spaces provided. More detailed instructions are given at the beginning of the different clauses of the ICS proforma.

---

## A.2 Identification of the User Equipment

Identification of the User Equipment should be filled in so as to provide as much detail as possible regarding version numbers and configuration options.

The product supplier information and client information should both be filled in if they are different.

A person who can answer queries regarding information supplied in the ICS should be named as the contact person.

### A.2.1 Date of the statement

.....

### A.2.2 User Equipment Under Test (UEUT) identification

UEUT name:

.....

.....

Hardware configuration:

.....

.....

.....

Software configuration:

.....

.....

.....

### A.2.3 Product supplier

Name:

.....

Address:

.....

.....

Telephone number:

.....

Facsimile number:

.....

E-mail address:

.....

Additional information:

.....

.....

.....

### A.2.4 Client

Name:

.....

Address:

.....

.....

.....

Telephone number:

.....

.....

Facsimile number:

.....

E-mail address:

.....

Additional information:

.....  
.....  
.....

## A.2.5 ICS contact person

Name:

.....

Telephone number:

.....

Facsimile number:

.....

E-mail address:

.....

Additional information:

.....  
.....

---

## A.3 Identification of the protocol

This ICS proforma applies to the 3GPP standards listed in the normative references clause of the present document.

---

## A.4 ICS proforma tables

### A.4.1 UE Implementation Types

**Table A.4.1-1: UE Radio Technologies**

Item	UE Radio Technologies	Ref.	Release	Mnemonic	Comments
1	NR FDD	38.101-1, 38.101-2	Rel-15	pc_nrFDD	
2	NR TDD	38.101-1, 38.101-2	Rel-15	pc_nrTDD	

**Table A.4.1-2: UE general functionality**

Item	UE Functionality	Ref.	Release	Mnemonic	Comments
1	Support of multiple NR FDD bands	38.101, 5.2	Rel-15	pc_nrFDD_MultiBand	
2	Support of multiple NR TDD bands	38.101, 5.2	Rel-15	pc_nrTDD_MultiBand	
3	NR SUL	38.101-1	Rel-15	pc_nrSUL	
4	NR SDL	38.101-1	Rel-15	pc_nrSDL	
5	Support of multiple NR SUL bands	38.101, 5.2	Rel-15	pc_nrSUL_MultiBand	
6	Support of multiple NR SDL bands	38.101, 5.2	Rel-15	pc_nrSDL_MultiBand	
7	Support of frequency range FR1	38.101-1 (cl. 5.1)	Rel-15	pc_nrFR1	
8	Support of frequency range FR2	38.101-2 (cl. 5.1)	Rel-15	pc_nrFR2	

**Table A.4.1-3: RAN-CN Interface Options**

Item	UE support of RAN-CN Interface Options	Ref.	Release	Mnemonic	Comments
1	NG-RAN NR	38.300	Rel-15	pc_NG_RAN_NR	Option 2
2	EN-DC	37.340	Rel-15	pc_EN_DC	Option 3
3	NE-DC	37.340	Rel-15	pc_NE_DC	Option 4
4	NG-RAN E-UTRA	38.300	Rel-15	pc_NG_RAN_EUTRA	Option 5
5	NGEN-DC	37.340	Rel-15	pc_NGEN_DC	Option 7

**Table A.4.1-4: NSA DC UE Radio Technologies**

Item	NSA UE Radio Technologies	Ref.	Release	Mnemonic	Comments
1	Intra-Band Contiguous EN-DC	38.101-3, 5.2B.2	Rel-15	pc_IntraBand_Contiguou_s_ENDC	
2	Intra-Band Non-Contiguous EN-DC	38.101-3, 5.2B.3	Rel-15	pc_IntraBand_Non_Cont iguous_ENDC	
3	Inter-Band EN-DC within FR1	38.101-3, 5.2B.4	Rel-15	pc_InterBand_ENDC_Wi thinFR1	
4	Inter-Band EN-DC including FR2	38.101-3, 5.2B.5	Rel-15	pc_InterBand_ENDC_In cludingFR2	
5	Inter-band EN-DC including both FR1 and FR2	38.101-3, 5.2B.6	Rel-15	pc_InterBand_ENDC_In cludingFR1_FR2	
6	Inter-band NR-DC between FR1 and FR2	38.101-3, 5.2B.6	Rel-15	pc_InterBand_NRDC_Be tweenFR1_FR2	

**Table A.4.1-4A: SA CA UE Radio Technologies**

Item	SA UE Radio Technologies	Ref.	Release	Mnemonic	Comments
1	Intra-Band Contiguous CA within FR1	38.101-1, 5.2A.1	Rel-15	pc_IntraBand_Contiguou_s_CA_WithinFR1	
2	Intra-Band Non-contiguous CA within FR1	38.101-1, 5.2A.1	Rel-15	pc_IntraBand_NonConti guous_CA_WithinFR1	
3	Intra-Band Contiguous CA within FR2	38.101-2, 5.2A.1	Rel-15	pc_IntraBand_Contiguou_s_CA_WithinFR2	
4	Intra-Band Non-contiguous CA within FR2	38.101-2, 5.2A.1	Rel-15	pc_IntraBand_NonConti guous_CA_WithinFR2	
5	Inter-Band CA within FR1	38.101-1, 5.2A.2	Rel-15	pc_InterBand_CA_Withi nFR1	
6	Inter-Band CA within FR2	38.101-2, 5.2A.2	Rel-15	pc_InterBand_CA_Withi nFR2	
7	Inter-band CA between FR1 and FR2	38.101-3, 5.2A.1	Rel-15	pc_InterBand_CA_Betw eenFR1_FR2	

**Table A.4.1-5: 5GS UE Core Technologies**

Item	5GS UE Core Technologies	Ref.	Release	Mnemonic	Comments
1	UE Supports 5G Core Network	24.501	Rel-15	pc_5GCN	
2	UE Supports 5G Core Network over non-3GPP Access Network	24.501, 4.7	Rel-15	pc_5GCN_N3AN	

## A.4.2 UE Service Capabilities

### A.4.2.1 3GPP Standardised UE Service Capabilities

#### A.4.2.1.1 Bearer Services

**Table A.4.2.1.1-1: Definition of Bearer Services**

Item	Definition of Bearer Services	Ref.	Release	Mnemonic	Comments
1	FFS				

## A.4.3 Baseline Implementation Capabilities

**Table A.4.3-1: Supported protocols**

Item	Supported protocols	Ref.	Release	Mnemonic	Comments
1	5GS Mobility Management	24.501	Rel-15		
2	5GS Session Management	24.501	Rel-15		
3	Radio Resource Control	38.331	Rel-15		
4	Service Data Adaptation Protocol	37.324	Rel-15		
5	Packet Data Convergence Protocol	38.323	Rel-15		
6	Radio Link Control	38.322	Rel-15		
7	Medium Access Control	38.321	Rel-15		
8	Physical Layer	38.201	Rel-15		

**Table A.4.3-2: Special Conformance Testing Functions**

Item	Special Conformance Testing Functions	Ref.	Release	Mnemonic	Comments
1	UE test loop	38.509	Rel-15		

### A.4.3.1 RF Baseline Implementation Capabilities

NOTE: The values indicated in column "Release" in tables A.4.3.1-1 and A.4.3.1-2 below are to be understood as the specifications release version in which a band was introduced and not as a mandate that a UE conforming to particular release shall support a particular band. For further guidance to release independent bands see TS 38.307 [19].

**Table A.4.3.1-1: NR FDD FR1 RF Baseline Implementation Capabilities**

Item	NR FDD RF Baseline Implementation Capabilities	Ref.	Release	Mnemonic	Comments
1	NR Frequency band: 1920-1980, 2110-2170 MHz	38.101-1, 5.2	Rel-15	pc_nrBand1_Supp	NR Band 1
2	NR Frequency band: 1850-1910, 1930-1990 MHz	38.101-1, 5.2	Rel-15	pc_nrBand2_Supp	NR Band 2
3	NR Frequency band: 1710-1785, 1805-1880 MHz	38.101-1, 5.2	Rel-15	pc_nrBand3_Supp	NR Band 3
4	NR Frequency band: 824-849, 869-894 MHz	38.101-1, 5.2	Rel-15	pc_nrBand5_Supp	NR Band 5
5	NR Frequency band: 2500-2570, 2620-2690 MHz	38.101-1, 5.2	Rel-15	pc_nrBand7_Supp	NR Band 7
6	NR Frequency band: 880-915, 925-960 MHz	38.101-1, 5.2	Rel-15	pc_nrBand8_Supp	NR Band 8
6a to 6c	Reserved				
6d	NR Frequency band: 699-716, 729-746 MHz	38.101-1, 5.2	Rel-15	pc_nrBand12_Supp	NR Band 12
7	NR Frequency band: 832-862, 791-821 MHz	38.101-1, 5.2	Rel-15	pc_nrBand20_Supp	NR Band 20
7a to 7d	Reserved				
7e	NR Frequency band: 1850-1915, 1930-1995 MHz	38.101-1, 5.2	Rel-15	pc_nrBand25_Supp	NR Band 25
8	NR Frequency band: 703-748, 758-803 MHz	38.101-1, 5.2	Rel-15	pc_nrBand28_Supp	NR Band 28
9	NR Frequency band: 1710-1780, 2110-2200 MHz	38.101-1, 5.2	Rel-15	pc_nrBand66_Supp	NR Band 66
10	NR Frequency band: 1695-1710, 1995-2020 MHz	38.101-1, 5.2	Rel-15	pc_nrBand70_Supp	NR Band 70
11	NR Frequency band: 663-698, 617-652 MHz	38.101-1, 5.2	Rel-15	pc_nrBand71_Supp	NR Band 71
12 to 13	Reserved				
14	NR Frequency band: 1427-1470, 1475-1518 MHz	38.101-1, 5.2	Rel-15	pc_nrBand74_Supp	NR Band 74

**Table A.4.3.1-2: NR TDD FR1 RF Baseline Implementation Capabilities**

Item	NR TDD RF Baseline Implementation Capabilities	Ref.	Release	Mnemonic	Comments
0	NR Frequency band: 2010-2025 MHz	38.101-1, 5.2	Rel-15	pc_nrBand34_Supp	NR Band 34
1	NR Frequency band: 2570-2620 MHz	38.101-1, 5.2	Rel-15	pc_nrBand38_Supp	NR Band 38
1a	NR Frequency band: 1880-1920 MHz	38.101-1, 5.2	Rel-15	pc_nrBand39_Supp	NR Band 39
1b	NR Frequency band: 2300-2400 MHz	38.101-1, 5.2	Rel-15	pc_nrBand40_Supp	NR Band 40
2	NR Frequency band: 2496-2690 MHz	38.101-1, 5.2	Rel-15	pc_nrBand41_Supp	NR Band 41
2a to 2h	Reserved				
2i	NR Frequency band: 1432-1517 MHz	38.101-1, 5.2	Rel-15	pc_nrBand50_Supp	NR Band 50
2k	NR Frequency band: 1427-1432 MHz	38.101-1, 5.2	Rel-15	pc_nrBand51_Supp	NR Band 51
3	NR Frequency band: 3300-4200 MHz	38.101-1, 5.2	Rel-15	pc_nrBand77_Supp	NR Band 77
4	NR Frequency band: 3300-3800 MHz	38.101-1, 5.2	Rel-15	pc_nrBand78_Supp	NR Band 78
5	NR Frequency band: 4400-5000 MHz	38.101-1, 5.2	Rel-15	pc_nrBand79_Supp	NR Band 79

**Table A.4.3.1-3: NR FR2 TDD RF Baseline Implementation Capabilities**

Item	NR TDD RF Baseline Implementation Capabilities	Ref.	Release	Mnemonic	Comments
1	NR Frequency band: 26500–29500 MHz	38.101-2, 5.2	Rel-15	pc_nrBand257_Supp	NR Band 257
2	NR Frequency band: 24250–27500 MHz	38.101-2, 5.2	Rel-15	pc_nrBand258_Supp	NR Band 258
3	NR Frequency band: 37000–40000 MHz	38.101-2, 5.2	Rel-15	pc_nrBand260_Supp	NR Band 260
4	NR Frequency band: 27500–28350 MHz	38.101-2, 5.2	Rel-15	pc_nrBand261_Supp	NR Band 261

**Table A.4.3.1-4: NR PC2 RF Baseline Implementation Capabilities**

Item	NR PC2 RF Baseline Implementation Capabilities	Ref.	Release	Mnemonic	Comments
1	NR Frequency band: 2496–2690 MHz	38.101-1, 6.2.1	Rel-15	pc_nrBand41_PC2_Supp	NR Band 41
2	NR Frequency band: 3300–4200 MHz	38.101-1, 6.2.1	Rel-15	pc_nrBand77_PC2_Supp	NR Band 77
3	NR Frequency band: 3300–3800 MHz	38.101-1, 6.2.1	Rel-15	pc_nrBand78_PC2_Supp	NR Band 78
4	NR Frequency band: 4400–5000 MHz	38.101-1, 6.2.1	Rel-15	pc_nrBand79_PC2_Supp	NR Band 79

**Table A.4.3.1-5: NR SUL FR1 RF Baseline Implementation Capabilities**

Item	NR SUL FR1 RF Baseline Implementation Capabilities	Ref.	Release	Mnemonic	Comments
1	NR Frequency band: 1710–1785 MHz	38.101-1, 5.2	Rel-15	pc_nrBand80_Supp	NR Band 80
2	NR Frequency band: 880–915 MHz	38.101-1, 5.2	Rel-15	pc_nrBand81_Supp	NR Band 81
3	NR Frequency band: 832–862 MHz	38.101-1, 5.2	Rel-15	pc_nrBand82_Supp	NR Band 82
4	NR Frequency band: 703–748 MHz	38.101-1, 5.2	Rel-15	pc_nrBand83_Supp	NR Band 83
5	NR Frequency band: 1920–1980 MHz	38.101-1, 5.2	Rel-15	pc_nrBand84_Supp	NR Band 84
6	NR Frequency band: 1710–1780 MHz	38.101-1, 5.2	Rel-15	pc_nrBand86_Supp	NR Band 86

**Table A.4.3.1-6: NR SDL FR1 RF Baseline Implementation Capabilities**

Item	NR SUL FR1 RF Baseline Implementation Capabilities	Ref.	Release	Mnemonic	Comments
1	NR Frequency band: 1432–1517 MHz	38.101-1, 5.2	Rel-15	pc_nrBand75_Supp	NR Band 75
2	NR Frequency band: 1427–1432 MHz	38.101-1, 5.2	Rel-15	pc_nrBand76_Supp	NR Band 76

### A.4.3.2 Physical Layer Baseline Implementation Capabilities

**Table A.4.3.2-1: UE Physical Layer Baseline Implementation Capabilities**

Item	UE Physical Layer Baseline Implementation Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support PDSCH reception based on semi-persistent scheduling	38.306, 4.2.7.10	Rel-15	pc_downlinkSPS	No		
2	Support 256QAM for PDSCH for FR1	38.306, 4.2.7.10	Rel-15	pc_pdsch_256QAM_FR1	Yes		
3	Support 256QAM for PDSCH for FR2	38.306, 4.2.7.2	Rel-15	pc_pdsch_256QAM_FR2	No		
4	Support 256QAM for PUSCH for FR1	38.306, 4.2.7.2	Rel-15	pc_pusch_256QAM_FR1	No		
5	Support receiving PDSCH using PDSCH mapping type A with less than seven symbols	38.306, 4.2.7.10	Rel-15	pc_pdsch_MappingTypeA	Yes		
6	Support receiving PDSCH using PDSCH mapping type B	38.306, 4.2.7.10	Rel-15	pc_pdsch_MappingTypeB	Yes		
7	Support resource allocation Type 0 for PUSCH	38.306, 4.2.7.10	Rel-15	pc_ra_Type0_PUSCH	No		
8	Support scaling factor 0.75 is applied to the band in the max data rate calculation	38.306, 4.2.7	Rel-15	pc_scalingFactor0dot75			
9	Support handover using a contention free random access on PRACH resources that are associated with CSI-RS resources of the target cell	38.306, 4.2.7.10	Rel-15	pc_csi_RS_CFRA_ForHO	No		
10	Support Type 1 PUSCH transmissions with configured grant	38.306, 4.2.7.10	Rel-15	pc_configuredUL_GrantType1	No		
11	Support Type 2 PUSCH transmissions with configured grant	38.306, 4.2.7.10	Rel-15	pc_configuredUL_GrantType2	No		
12	Support PDSCH Reception when configured with higher layer parameter aggregationFactorDL > 1	38.306, 4.2.7.10	Rel-15	pc_pdsch_RepetitionMultiSlots	No		
13	Supports supplemental uplink with dynamic switch (DCI based selection of PUSCH carrier)	38.306, 4.2.7.7	Rel-15	pc_dynamicSwitchSUL	No		
14	Supports more than one MIMO layers at the UE for PUSCH transmission with codebook precoding. UE indicating support of this feature shall also indicate support of PUSCH codebook coherency subset	38.306, 4.2.7.8	Rel-15	pc_nrMIMO_CB_PUSCH	No		Set to true if maxNumberMIMO-LayersCB-PUSCH has value other than 'oneLayer'
15	Supports more than one MIMO layers at the UE for PUSCH transmission using non-codebook precoding	38.306, 4.2.7.8	Rel-15	pc_nrMIMO_NonCB_PUSCH	No		Set to true if maxNumberMIMO-LayersNonCB-PUSCH has value other than 'oneLayer'
16	Support receiving PDSCH with interleaved VRB-to-PRB mapping	38.306, 4.2.7.10	Rel-15	pc_interleavingVRB_ToPRB_PDSCH	Yes		

17	Support dynamic EN-DC power sharing	38.306, 4.2.7.9	Rel-15	pc_dynamicPowerSharing	Yes		If the UE supports this capability it will dynamically share the power between NR and LTE if P_LTE + P_NR > Pcmax.
18	Supports up to 10 search spaces in a SCell per BWP	38.306, 4.2.7.10	Rel-15	pc_maxNumberSearchSpaces	No		
19	Supports spatial bundling of HARQ-ACK bits carried on PUCCH or PUSCH per PUCCH group. With spatial bundling, two HARQ-ACK bits for a DL MIMO data is bundled into a single bit by logical "AND" operation	38.306, 4.2.7.10	Rel-15	pc_spatialBundlingHARQ_ACK	Yes		
20	Support alternative additional DMRS position for co-existence with LTE CRS	38.306, 4.2.7.5	Rel-15	pc_additionalDMRS_DL_Alt	No		
21	Supports transmitting PUSCH scheduled by DCI format 0_0 or 0_1 when configured with higher layer parameter aggregationFactorIUL > 1	38.306, 4.2.7.10	Rel-15	pc_pusch_RepetitionMultiSlots	Yes		

#### A.4.3.2A NR CA Physical Layer Baseline Implementation Capabilities

##### A.4.3.2A.1 General NR CA capabilities

**Table A.4.3.2A.1-1: Downlink NR CA capabilities (for one or more of the supported NR CA configurations in Tables A.4.3.2A.2.1-3, A.4.3.2A.2.2-3, A.4.3.2A.3.2-3 and A.4.3.2A.4-3)**

Item	Bandwidth Class	Ref.	Comments
1	DL NR CA with 2 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
2	DL NR CA with 3 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
3	DL NR CA with 4 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
4	DL NR CA with 5 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
5	DL NR CA with 6 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
6	DL NR CA with 7 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
7	DL NR CA with 8 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	

**Table A.4.3.2A.1-2: Uplink CA capabilities (for one or more of the supported NR CA configurations in Tables A.4.3.2A.2.1-3, A.4.3.2A.2.2-3, A.4.3.2A.3.2-3 and A.4.3.2A.4-3)**

Item	Bandwidth Class	Ref.	Comments
1	UL NR CA with 2 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
2	UL NR CA with 3 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
3	UL NR CA with 4 carriers	38.101-1, 5.3A 38.101-2, 5.3A 38.101-3, 5.3A	
4	UL NR CA with 5 carriers	38.101-2, 5.3A 38.101-3, 5.3A	
5	UL NR CA with 6 carriers	38.101-2, 5.3A 38.101-3, 5.3A	
6	UL NR CA with 7 carriers	38.101-2, 5.3A 38.101-3, 5.3A	
7	UL NR CA with 8 carriers	38.101-2, 5.3A 38.101-3, 5.3A	

## A.4.3.2A.2 NR CA Intra-band contiguous

### A.4.3.2A.2.1 NR CA Intra-band contiguous with FR1

**Table A.4.3.2A.2.1-1: Downlink Bandwidth Class capabilities for NR Intra-band contiguous CA with FR1 configurations (for one or more of the supported configurations in Table A.4.3.2A.2.1-3)**

Item	Bandwidth Class	Ref.	Comments
1	DL NR FR1 Intra-band contiguous CA BW Class A	38.101-1, 5.3A.5	
2	DL NR FR1 Intra-band contiguous CA BW Class B	38.101-1, 5.3A.5	
3	DL NR FR1 Intra-band contiguous CA BW Class C	38.101-1, 5.3A.5	
4	DL NR FR1 Intra-band contiguous CA BW Class D	38.101-1, 5.3A.5	
5	DL NR FR1 Intra-band contiguous CA BW Class E	38.101-1, 5.3A.5	
6	DL NR FR1 Intra-band contiguous CA BW Class F	38.101-1, 5.3A.5	
7	DL NR FR1 Intra-band contiguous CA BW Class G	38.101-1, 5.3A.5	
8	DL NR FR1 Intra-band contiguous CA BW Class H	38.101-1, 5.3A.5	
9	DL NR FR1 Intra-band contiguous CA BW Class I	38.101-1, 5.3A.5	
10	DL NR FR1 Intra-band contiguous CA BW Class J	38.101-1, 5.3A.5	
11	DL NR FR1 Intra-band contiguous CA BW Class K	38.101-1, 5.3A.5	
12	DL NR FR1 Intra-band contiguous CA BW Class L	38.101-1, 5.3A.5	

**Table A.4.3.2A.2.1-2: Uplink Bandwidth Class capabilities for NR Intra-band contiguous CA with FR1 configurations (for one or more of the supported configurations in Table A.4.3.2A.2.1-3)**

Item	Bandwidth Class	Ref.	Comments
1	UL NR FR1 Intra-band contiguous CA BW Class A	38.101-1, 5.3A.5	
2	UL NR FR1 Intra-band contiguous CA BW Class B	38.101-1, 5.3A.5	
3	UL NR FR1 Intra-band contiguous CA BW Class C	38.101-1, 5.3A.5	
4	UL NR FR1 Intra-band contiguous CA BW Class D	38.101-1, 5.3A.5	
5	UL NR FR1 Intra-band contiguous CA BW Class E	38.101-1, 5.3A.5	
6	UL NR FR1 Intra-band contiguous CA BW Class F	38.101-1, 5.3A.5	
7	UL NR FR1 Intra-band contiguous CA BW Class G	38.101-1, 5.3A.5	
8	UL NR FR1 Intra-band contiguous CA BW Class H	38.101-1, 5.3A.5	
9	UL NR FR1 Intra-band contiguous CA BW Class I	38.101-1, 5.3A.5	
10	UL NR FR1 Intra-band contiguous CA BW Class J	38.101-1, 5.3A.5	
11	UL NR FR1 Intra-band contiguous CA BW Class K	38.101-1, 5.3A.5	
12	UL NR FR1 Intra-band contiguous CA BW Class L	38.101-1, 5.3A.5	

**Table A.4.3.2A.2.1-3: Supported NR CA configurations for Intra-band contiguous CA with FR1**

NR CA configuration / Item (Note 1)	Release	Supported	Supported CA Bandwidth Class(es) in UL (Note 2,5)	Supported Bandwidth Combination Set(s) (Note 3)
CA_n41C	Rel-16			
CA_n66B	Rel-16			
CA_n71B	Rel-16			
CA_n77C	Rel-15			
CA_n78C	Rel-15			
CA_n79C	Rel-15			
CA_n77D	Rel-15			
CA_n78D	Rel-15			
CA_n79D	Rel-15			
CA_n77E	Rel-15			
CA_n78E	Rel-15			
CA_n79E	Rel-15			

Note 1: Notation used for intra-band contiguous CA Bands is according to TS 38.101-1 [23] Table 5.5A.1-1, e.g. 'CA\_n77C' indicates CA operation on NR band n77 with DL CA Bandwidth Class C.

Note 2: The UL CA capabilities as per Table A.4.3.2A.1-2 can be supported on a single or multiple CA Band(s). The UE supplier shall indicate all supported UL CA Bandwidth Class(es), in uplink of the supported CA Band(s), as per TS 38.101-1 [23] Table 5.5A.1-1. For this release of specification valid choices are 'N', 'nXB' and 'nXC', where X is the band. For example, for CA\_n1B, N would mean only DL CA, 'n1B' would mean both DL and UL CA.

Note 3: The UE supplier shall indicate the supported Bandwidth Combination Set(s) as per TS 38.101-1 [23] Table 5.5A.1-1.

Note 4: Reference to all items is 38.101-1, 5.5A.1 and 38.331, 6.3.4

Note 5: UL(Table A.4.3.2A.2.1-3) shall return all supported CA Configurations where at least one UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".

UL\_2CC(Table A.4.3.2A.2.1-3) shall return all supported CA Configurations where at least one 2 Carrier UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".

UL\_3CC(Table A.4.3.2A.2.1-3) shall return all supported CA Configurations where at least one 3 Carrier UL CA Bandwidth Class was declared.

## A.4.3.2A.2.2 NR CA Intra-band contiguous with FR2

**Table A.4.3.2A.2.2-1: Downlink Bandwidth Class capabilities for NR Intra-band contiguous CA with FR2 configurations (for one or more of the supported configurations in Table A.4.3.2A.2.2-3)**

Item	Bandwidth Class	Ref.	Comments
1	DL NR FR2 Intra-band contiguous CA BW Class A	38.101-2, 5.3A.4	
2	DL NR FR2 Intra-band contiguous CA BW Class B	38.101-2, 5.3A.4	
3	DL NR FR2 Intra-band contiguous CA BW Class C	38.101-2, 5.3A.4	
4	DL NR FR2 Intra-band contiguous CA BW Class D	38.101-2, 5.3A.4	
5	DL NR FR2 Intra-band contiguous CA BW Class E	38.101-2, 5.3A.4	
6	DL NR FR2 Intra-band contiguous CA BW Class F	38.101-2, 5.3A.4	
7	DL NR FR2 Intra-band contiguous CA BW Class G	38.101-2, 5.3A.4	
8	DL NR FR2 Intra-band contiguous CA BW Class H	38.101-2, 5.3A.4	
9	DL NR FR2 Intra-band contiguous CA BW Class I	38.101-2, 5.3A.4	
10	DL NR FR2 Intra-band contiguous CA BW Class J	38.101-2, 5.3A.4	
11	DL NR FR2 Intra-band contiguous CA BW Class K	38.101-2, 5.3A.4	
12	DL NR FR2 Intra-band contiguous CA BW Class L	38.101-2, 5.3A.4	
13	DL NR FR2 Intra-band contiguous CA BW Class M	38.101-2, 5.3A.4	
14	DL NR FR2 Intra-band contiguous CA BW Class O	38.101-2, 5.3A.4	
15	DL NR FR2 Intra-band contiguous CA BW Class P	38.101-2, 5.3A.4	
16	DL NR FR2 Intra-band contiguous CA BW Class Q	38.101-2, 5.3A.4	

**Table A.4.3.2A.2.2-2: Uplink Bandwidth Class capabilities for NR Intra-band contiguous CA with FR2 configurations (for one or more of the supported configurations in Table A.4.3.2A.2.2-3)**

Item	Bandwidth Class	Ref.	Comments
1	UL NR FR1 Intra-band contiguous CA BW Class B	38.101-2, 5.3A.4	
2	UL NR FR1 Intra-band contiguous CA BW Class C	38.101-2, 5.3A.4	
3	UL NR FR1 Intra-band contiguous CA BW Class D	38.101-2, 5.3A.4	
4	UL NR FR1 Intra-band contiguous CA BW Class E	38.101-2, 5.3A.4	
5	UL NR FR1 Intra-band contiguous CA BW Class F	38.101-2, 5.3A.4	
6	UL NR FR1 Intra-band contiguous CA BW Class G	38.101-2, 5.3A.4	
7	UL NR FR1 Intra-band contiguous CA BW Class H	38.101-2, 5.3A.4	
8	UL NR FR1 Intra-band contiguous CA BW Class I	38.101-2, 5.3A.4	
9	UL NR FR1 Intra-band contiguous CA BW Class J	38.101-2, 5.3A.4	
10	UL NR FR1 Intra-band contiguous CA BW Class K	38.101-2, 5.3A.4	
11	UL NR FR1 Intra-band contiguous CA BW Class L	38.101-2, 5.3A.4	
12	UL NR FR1 Intra-band contiguous CA BW Class M	38.101-2, 5.3A.4	
13	UL NR FR1 Intra-band contiguous CA BW Class O	38.101-2, 5.3A.4	
14	UL NR FR1 Intra-band contiguous CA BW Class P	38.101-2, 5.3A.4	
15	UL NR FR1 Intra-band contiguous CA BW Class Q	38.101-2, 5.3A.4	

**Table A.4.3.2A.2.2-3: Supported NR CA configurations for Intra-band contiguous CA with FR2**

NR CA configuration / Item (Note 1)	Release	Supported	Supported CA Bandwidth Class(es) in UL (Note 2,5)	Supported Bandwidth Combination Set(s) (Note 3)
CA_n257G	Rel-16			
CA_n257H	Rel-16			
CA_n257I	Rel-16			

Note 1: Notation used for intra-band contiguous CA Bands is according to TS 38.101-2 [x1] Table 5.5A.1-1, e.g. 'CA\_n257C' indicates CA operation on NR band n257 with DL CA Bandwidth Class C.

Note 2: The UL CA capabilities as per Table A.4.3.2A.2.2-2 can be supported on a single or multiple CA Band(s). The UE supplier shall indicate all supported UL CA Bandwidth Class(es), in uplink of the supported CA Band(s), as per TS 38.101-2 [x1] Table 5.5A.1-1. For this release of specification valid choices are 'N', 'XB' and 'XC', where X is the band. For example, for CA\_1C, N would mean only DL CA, '1C' would mean both DL and UL CA.

Note 3: The UE supplier shall indicate the supported Bandwidth Combination Set(s) as per TS 38.101-2 [x1] Table 5.5A.1-1.

Note 4: Reference to all items is 38.101-2, 5.5A.1 and 38.331, 6.3.4

Note 5: UL(Table A.4.3.2A.2.2-3) shall return all supported CA Configurations where at least one UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".  
 UL\_2CC(Table A.4.3.2A.2.2-3) shall return all supported CA Configurations where at least one 2 Carrier UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".  
 UL\_3CC(Table A.4.3.2A.2.2-3) shall return all supported CA Configurations where at least one 3 Carrier UL CA Bandwidth Class was declared.

#### A.4.3.2A.3 NR CA Intra-band non-contiguous

##### A.4.3.2A.3.1 NR CA Intra-band non-contiguous with FR1

**Table A.4.3.2A.3.1-1: Downlink Bandwidth Class capabilities for NR Intra-band non-contiguous configurations CA with FR1 (for one or more of the supported configurations in Table A.4.3.2A.3.1-3)**

Item	Bandwidth Class	Ref.	Comments
1	DL NR FR1 Intra-band non-contiguous CA BW Class Combination A-A	38.101-2, 5.3A.5	

**Table A.4.3.2A.3.1-2: Uplink Bandwidth Class capabilities for NR Intra-band non-contiguous CA with FR1 configurations (for one or more of the supported configurations in Table A.4.3.2A.3.1-3)**

Item	Bandwidth Class	Ref.	Comments
1	UL NR FR1 Intra-band non-contiguous CA BW Class Combination A-A	38.101-2, 5.3A.5	

**Table A.4.3.2A.3.1-3: Supported NR CA configurations for Intra-band non-contiguous CA with FR1**

NR CA configuration / Item	Release	Supported	Supported CA Bandwidth Class(es) in UL (Note 3)	Supported Bandwidth Combination Set(s) (Note 1)
CA_n66(2A)	Rel-16			

Note 1: The UE supplier shall indicate the supported Bandwidth Combination Set(s) as per TS 38.101-1 [23] Table 5.5A.2-1.

Note 2: Reference to all items is 38.101-1 [23], 5.5A.2 and 38.331, 6.3.4

Note 3: UL(Table A.4.3.2A.3.1-3) shall return all supported CA Configurations where at least one UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".

UL\_2CC(Table A.4.3.2A.3.1-3) shall return all supported CA Configurations where at least one 2 Carrier UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".

UL\_3CC(Table A.4.3.2A.3.1-3) shall return all supported CA Configurations where at least one 3 Carrier UL CA Bandwidth Class was declared.

##### A.4.3.2A.3.2 NR CA Intra-band non-contiguous with FR2

**Table A.4.3.2A.3.2-1: Downlink Bandwidth Class capabilities for NR Intra-band non-contiguous configurations CA with FR2 (for one or more of the supported configurations in Table A.4.3.2A.3.2-3)**

Item	Bandwidth Class	Ref.	Comments
1	DL NR FR2 Intra-band non-contiguous CA BW Class Combination A-A	38.101-2, 5.3A.5	

**Table A.4.3.2A.3.2-2: Uplink Bandwidth Class capabilities for NR Intra-band non-contiguous CA with FR2 configurations (for one or more of the supported configurations in Table A.4.3.2A.3.2-3)**

Item	Bandwidth Class	Ref.	Comments
1	UL NR FR1 Intra-band non-contiguous CA BW Class Combination A-A	38.101-2, 5.3A.5	

**Table A.4.3.2A.3.2-3: Supported configurations for NR Intra-band non-contiguous CA with FR2 FFS**

#### A.4.3.2A.4 NR Inter-band CA

##### A.4.3.2A.4.1 NR Inter-band CA with FR1 (two bands)

**Table A.4.3.2A.4.1-1: Downlink Bandwidth Class Combination capabilities for NR Inter-band CA configuration with FR1 and two bands (for one or more of the supported CA configurations in Table A.4.3.2A.4.1-3)**

Item	Bandwidth Class	Ref.	Comments
1	DL NR FR1 Inter-band CA BW Class Combination A-A (two bands)	38.101-2, 5.3A.5	

**Table A.4.3.2A.4.1-2: Uplink Bandwidth Class Combination capabilities for NR Inter-band CA with FR1 and two bands (for one or more of the supported CA configurations in Table A.4.3.2A.4.1-3)**

Item	Bandwidth Class	Ref.	Comments
1	UL NR FR1 Inter-band CA BW Class Combination A-A (two bands)	38.101-2, 5.3A.5	

**Table A.4.3.2A.4.1-3: Supported CA configurations for NR Inter-band CA with FR1 and two bands**

NR CA configuration / Item (Note 1)	Release	Supported	Supported CA Bandwidth Class(es) in UL (Note 2,5)	Supported Bandwidth Combination Set(s) (Note 3)
CA_n66A-n70A	Rel-16			
CA_n66B-n70A	Rel-16			
CA_n66(2A)-n70	Rel-16			
CA_n66A-n71A	Rel-16			
CA_n66(2A)-n71A	Rel-16			
CA_n70A-n71A	Rel-16			

Note 1: Notation used for intra-band contiguous CA Bands is according to TS 38.101-1 [23] Table 5.5A.1-1, e.g. 'CA\_n77C' indicates CA operation on NR band n77 with DL CA Bandwidth Class C.

Note 2: The UL CA capabilities as per Table A.4.3.2A.1-2 can be supported on a single or multiple CA Band(s). The UE supplier shall indicate all supported UL CA Bandwidth Class(es), in uplink of the supported CA Band(s), as per TS 38.101-1 [23] Table 5.5A.1-1. For this release of specification valid choices are 'N', 'nXB' and 'nXC', where X is the band. For example, for CA\_n1B, N would mean only DL CA, 'n1B' would mean both DL and UL CA.

Note 3: The UE supplier shall indicate the supported Bandwidth Combination Set(s) as per TS 38.101-1 [23] Table 5.5A.3-1.

Note 4: Reference to all items is 38.101-1 [23], 5.5A.3 and 38.331, 6.3.4

Note 5: UL(Table A.4.3.2A.4.1-3) shall return all supported CA Configurations where at least one UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".

UL\_2CC(Table A.4.3.2A.4.1-3) shall return all supported CA Configurations where at least one 2 Carrier UL CA Bandwidth Class was declared in column "Supported CA Bandwidth Class(es) in UL".

UL\_3CC(Table A.4.3.2A.4.1-3) shall return all supported CA Configurations where at least one 3 Carrier UL CA Bandwidth Class was declared.

## A.4.3.2B NR DC Physical Layer Baseline Implementation Capabilities

### A.4.3.2B.1 NR DC between FR1 and FR2

**Table A.4.3.2B.1-1: Downlink NR DC Bandwidth Class Combination capabilities between FR1 and FR2 (for one or more of the supported DC configurations in Table A.4.3.2B.1-2)**

Item	Bandwidth Class (FR1-FR2)	Ref.	Comments
1	DL NR DC FR1 and FR2 BW Class Combination A-A	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
2	DL NR DC FR1 AND FR2 BW Class Combination A-D	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
3	DL NR DC FR1 AND FR2 BW Class Combination A-E	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
4	DL NR DC FR1 AND FR2 BW Class Combination A-F	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
5	DL NR DC FR1 AND FR2 BW Class Combination A-G	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
6	DL NR DC FR1 AND FR2 BW Class Combination A-H	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
7	DL NR DC FR1 AND FR2 BW Class Combination A-I	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
8	DL NR DC FR1 AND FR2 BW Class Combination A-J	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
9	DL NR DC FR1 AND FR2 BW Class Combination A-K	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
10	DL NR DC FR1 AND FR2 BW Class Combination A-L	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
11	DL NR DC FR1 AND FR2 BW Class Combination A-M	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
12	DL NR DC FR1 AND FR2 BW Class Combination C-A	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
13	DL NR DC FR1 AND FR2 BW Class Combination C-D	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
14	DL NR DC FR1 AND FR2 BW Class Combination C-E	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	
15	DL NR DC FR1 AND FR2 BW Class Combination C-F	38.101-1, 5.3A.5 38.101-2, 5.3A.4 38.101-3, 5.3A.1	

**Table A.4.3.2B.1-2: Supported NR DC configurations between FR1 and FR2 (two bands)**

FFS

#### A.4.3.2B.2 EN-DC Physical Layer Baseline Implementation Capabilities

##### A.4.3.2B.2.1 EN-DC Intra-band contiguous with NR FR1

**Table A.4.3.2B.2.1-1: Bandwidth Class Combination capabilities for EN-DC Intra-band contiguous configurations with NR FR1 (for one or more of the supported configurations in Table A.4.3.2B.2.1-2)**

Item	Bandwidth Class (E-UTRA/NR FR1)	Ref.	Comments
1	DL EN-DC Intra-band contiguous with NR FR1 BW Class Combination A/A	38.101-3, 5.3B	
2	DL EN-DC Intra-band contiguous with NR FR1 BW Class Combination C/A	38.101-3, 5.3B	
3	DL EN-DC Intra-band contiguous with NR FR1 BW Class Combination D/A	38.101-3, 5.3B	

**Table A.4.3.2B.2.1-2: Supported EN-DC Intra-band contiguous configurations with NR FR1**

FFS

##### A.4.3.2B.2.2 EN-DC Intra-band non-contiguous with FR1

**Table A.4.3.2B.2.2-1: Bandwidth Class Combination capabilities for EN-DC Intra-band non-contiguous configurations with NR FR1 (for one or more of the supported configurations in Table A.4.3.2B.2.2-2)**

Item	Bandwidth Class (E-UTRA/NR FR1)	Ref.	Comments
1	DL EN-DC Intra-band non-contiguous with NR FR1 BW Class Combination A/A	36.101, 5.6A 38.101-1, 5.3A.5	
2	DL EN-DC Intra-band non-contiguous with NR FR1 BW Class Combination C/A	36.101, 5.6A 38.101-1, 5.3A.5	
3	DL EN-DC Intra-band non-contiguous with NR FR1 BW Class Combination D/A	36.101, 5.6A 38.101-1, 5.3A.5	

**Table A.4.3.2B.2.2-2: Supported EN-DC Intra-band non-contiguous configurations with NR FR1**

FFS

##### A.4.3.2B.2.3 EN-DC Inter-band

###### A.4.3.2B.2.3.1 EN-DC Inter-band with FR1 (two bands)

**Table A.4.3.2B.2.3.1-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR1 and two bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.1-2)**

Item	Bandwidth Class (E-UTRA/NR FR1)	Ref.	Comments
1	EN-DC Inter-band with NR FR1 BW Class Combination A/A (two bands)	36.101, 5.6A 38.101-1, 5.3A.5	
2	EN-DC Inter-band with NR FR1 BW Class Combination A/C (two bands)	36.101, 5.6A 38.101-1, 5.3A.5	
3	EN-DC Inter-band with NR FR1 BW Class Combination A-A/A (two bands)	36.101, 5.6A 38.101-1, 5.3A.5	

**Table A.4.3.2B.2.3.1-2: Supported EN-DC Inter-band configurations with NR FR1 (two bands)**

EN-DC configuration / Item	Release	Supported	Supported CA Bandwidth Class(es) in UL	Supported Bandwidth Combination Set(s)
DC_1A_n78A	Rel-15			
DC_1A_n79A	Rel-15			
DC_3A_n78A	Rel-15			
DC_3A_n79A	Rel-15			
DC_19A_n78A	Rel-15			
DC_19A_n79A	Rel-15			
DC_21A_n78A	Rel-15			
DC_21A_n79A	Rel-15			

## A.4.3.2B.2.3.2 EN-DC Inter-band with FR1 (three bands)

**Table A.4.3.2B.2.3.2-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR1 and three bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.2-2)**

Item	Bandwidth Class (E-UTRA/NR FR1)	Ref.	Comments
1	EN-DC Inter-band with NR FR1 BW Class Combination A/C (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
2	EN-DC Inter-band with NR FR1 BW Class Combination C/A (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
3	EN-DC Inter-band with NR FR1 BW Class Combination A/A/A (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
4	EN-DC Inter-band with NR FR1 BW Class Combination A/A/C (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
5	EN-DC Inter-band with NR FR1 BW Class Combination A-C/A (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
6	EN-DC Inter-band with NR FR1 BW Class Combination A-D/A (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
7	EN-DC Inter-band with NR FR1 BW Class Combination A-E/A (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
8	EN-DC Inter-band with NR FR1 BW Class Combination A/nAA (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	
9	EN-DC Inter-band with NR FR1 BW Class Combination A/A-A (three bands)	36.101, 5.6A 38.101-1, 5.3A.5	

**Table A.4.3.2B.2.3.2-2: Supported EN-DC Inter-band configurations with NR FR1 (three bands)**

FFS

## A.4.3.2B.2.3.3 EN-DC Inter-band with FR1 (four bands)

**Table A.4.3.2B.2.3.3-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR1 and four bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.3-2)**

FFS

**Table A.4.3.2B.2.3.3-2: Supported EN-DC Inter-band configurations with NR FR1 (four bands)**

FFS

A.4.3.2B.2.3.4 EN-DC Inter-band with FR1 (five bands)

**Table A.4.3.2B.2.3.4-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR1 and five bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.4-2)**

FFS

**Table A.4.3.2B.2.3.4-2: Supported EN-DC Inter-band configurations with NR FR1 (five bands)**

FFS

A.4.3.2B.2.3.5 EN-DC Inter-band with FR1 (six bands)

**Table A.4.3.2B.2.3.5-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR1 and six bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.5-2)**

FFS

**Table A.4.3.2B.2.3.5-2: Supported EN-DC Inter-band configurations with NR FR1 (six bands)**

FFS

A.4.3.2B.2.3.6 EN-DC Inter-band with FR2 (two bands)

**Table A.4.3.2B.2.3.6-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR2 and two bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.6-2)**

FFS

**Table A.4.3.2B.2.3.6-2: Supported EN-DC Intra-band non-contiguous configurations with NR FR2 (two bands)**

FFS

A.4.3.2B.2.3.7 EN-DC Inter-band with FR2 or with both FR1 and FR2 (three bands)

**Table A.4.3.2B.2.3.7-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR2, or with both FR1 and FR2, and three bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.7-2)**

FFS

**Table A.4.3.2B.2.3.7-2: Supported EN-DC Intra-band non-contiguous configurations with NR FR2, or with both FR1 and FR2 (three bands)**

FFS

A.4.3.2B.2.3.8 EN-DC Inter-band with FR2 or with both FR1 and FR2 (four bands)

**Table A.4.3.2B.2.3.8-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR2, or with both FR1 and FR2, and four bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.8-2)**

FFS

**Table A.4.3.2B.2.3.8-2: Supported EN-DC Intra-band non-contiguous configurations with NR FR2, or with both FR1 and FR2 (four bands)**

FFS

A.4.3.2B.2.3.9 EN-DC Inter-band with FR2 or with both FR1 and FR2 (five bands)

**Table A.4.3.2B.2.3.9-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR2, or with both FR1 and FR2, and five bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.9-2)**

FFS

**Table A.4.3.2B.2.3.9-2: Supported EN-DC Intra-band non-contiguous configurations with NR FR2, or with both FR1 and FR2 (five bands)**

FFS

A.4.3.2B.2.3.10 EN-DC Inter-band with FR2 or with both FR1 and FR2 (six bands)

**Table A.4.3.2B.2.3.10-1: Bandwidth Class Combination capabilities for EN-DC Inter-band with NR FR2, or with both FR1 and FR2, and six bands (for one or more of the supported DC configurations in Table A.4.3.2B.2.3.10-2)**

FFS

**Table A.4.3.2B.2.3.10-2: Supported EN-DC Intra-band non-contiguous configurations with NR FR2, or with both FR1 and FR2 (six bands)**

FFS

### A.4.3.3 PDCP Implementation Capabilities

**Table A.4.3.3-1: UE PDCP Implementation Capabilities**

Item	UE PDCP Implementation Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support 12 bit length of PDCP sequence number	38.306, 4.2.4	Rel-15	pc_shortSN	Yes		
2	Supports Out of order delivery of data to upper layers by PDCP	38.306, 4.2.4	Rel-15	pc_outOfOrderDelivery	No		

### A.4.3.4 RLC Implementation Capabilities

**Table A.4.3.4-1: UE RLC Implementation Capabilities**

Item	UE RLC Implementation Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support RLC AM with 12 bit length of RLC sequence number	38.306, 4.2.5	Rel-15	pc_am_WithShortSN	Yes		
2	Support RLC UM with 12 bit length of RLC sequence number	38.306, 4.2.5	Rel-15	pc_um_WithLongSN	Yes		
3	Support RLC UM with 6 bit length of RLC sequence number	38.306, 4.2.5	Rel-15	pc_um_WithShortSN	Yes		

### A.4.3.5 MAC Implementation Capabilities

**Table A.4.3.5-1: UE MAC Implementation Capabilities**

Item	UE MAC Implementation Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support long DRX cycle	38.306, 4.2.6	Rel-15	pc_longDRX_Cycle	Yes		
2	Support short DRX cycle	38.306, 4.2.6	Rel-15	pc_shortDRX_Cycle	Yes		
3	Support skipping of UL transmission for an uplink grant indicated on PDCCH if no data is available for transmission	38.306, 4.2.6	Rel-15	pc_skipUplinkTxDynamic	No		
4	Supports the logicalChannelSR-DelayTimer	38.306, 4.2.6	Rel-15	pc_logicalChannelSR_DelayTimer	No		

### A.4.3.6 Measurement Capabilities

**Table A.4.3.6-1: UE Measurement Capabilities**

Item	UE Measurement Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support NR measurements and events A triggered reporting	38.306, 4.2.9	Rel-15	pc_eventA_MeasAndReport	Yes		
2	Support two independent measurement gap configurations for FR1 and FR2	38.306, 4.2.9	Rel-15	pc_independentGapConfig	No		
3	Support NR intra-frequency and inter-frequency measurements and at least periodical reporting	38.306, 4.2.9	Rel-15	pc_intraAndInterF_MeasAndReport	Yes		
4	Support CSI-RSRP and CSI-RSRQ measurement as specified in TS38.215 [21], where CSI-RS resource is configured with an associated SS/PBCH	38.306, 4.2.9	Rel-15	pc_csi_RSRP_AndRSRQ_MeasWithSSB	No		
5	Support inter-RAT E-UTRA measurements and events B triggered reporting	38.306, 4.2.9	Rel-15	pc_eventB_MeasAndReport	Yes		
6	Support SS-SINR measures	38.306, 4.2.9	Rel-15	pc_ss_SINR_Meas	No		

### A.4.3.7 General Capabilities

**Table A.4.3.7-1: UE General Capabilities**

Item	UE General Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support UL transmission via either MCG path or SCG path for the split SRB as specified in TS 37.340[20]	38.306, 4.2.2	Rel-15	pc_splitSRB_WithOneUL_Path	No		
2	Support UL transmission via both MCG path and SCG path for the split DRB as specified in TS 37.340[20]	38.306, 4.2.2	Rel-15	pc_splitDRB_withUL_Both_MCG_SC	Yes		
3	Support direct SRB between the SN and the UE as specified in TS 37.340[20]	38.306, 4.2.2	Rel-15	pc_srb3	Yes		
4	Support of reflective QoS	38.306, 4.2.2	Rel-15	pc_as_Reflective_QoS	No		
5	Support of NAS reflective QoS	24.501, 6.2.5.1.4.1, 9.11.4.1	Rel-15	pc_nas_Reflective_QoS	No		
6	Support of SMS over NAS	24.501, 5.5.1.2	Rel-15	pc_sms_over_NAS	No		
7	Support of CMAS message on NR	38.331, 5.2.2.2	Rel-15	pc_CMAS_NR	No		
8	Support of ETWS message on NR	38.331, 5.2.2.2	Rel-15	pc_ETWS_NR	No		
9	The UE supports additional UE-requested PDU establishment	24.501, 6.4.1.5	Rel-15	pc_Additional_PDU_establishment	No		pc_ExpectedNoOfPDUSessionsAtRregistration +1
10	The UE includes the SM PDU DN request container IE in the PDU SESSION ESTABLISHMENT REQUEST message	24.501, 6.4.1.2	Rel-15	pc_SM_PDU_DN_RequestContainer	No		
11	Support of emergency services fallback	24.501, 9.11.3.5	Rel-15	pc_EmergencyService_fallback	No		
12	Support of EPS fallback	24.501, 9.11.3.5	Rel-15	pc_EPS_fallback	No		

### A.4.3.8 Mobility Capabilities

**Table A.4.3.8-1: UE Mobility Capabilities**

Item	UE Mobility Capabilities	Ref.	Release	Mnemonic	M	If indicated "Yes" the feature shall be implemented and successfully tested for the corresponding release	Comments
1	Support inter-RAT Handover to EUTRA connected to EPC	38.306, 4.2.9	Rel-15	pc_interRAT_EUTRA_Handover	Yes		
2	Support inter-frequency Handover from the corresponding duplex mode or from the corresponding frequency range.	38.306, 4.2.9	Rel-15	pc_handoverInterF	Yes		
3	Support Handover between FR1 and FR2	38.306, 4.2.9	Rel-15	pc_FR1toFR2_Handover	Yes		
4	Support Handover between FDD and TDD	38.306, 4.2.9	Rel-15	pc_FDDtoTDD_Handover	Yes		
5	Support inter-RAT Handover to E-UTRA connected to 5GC	38.306, 4.2.9	Rel-15	pc_interRAT_eLTE_Handover	Yes		

### A.4.3.9 Additional capabilities for UE declared capability

**Table A.4.3.9-1:** UE declared capabilities

Item	UE declared capabilities	Ref.	Release	Mnemonic	Comments
1	Enhanced Type X Receiver for NR	38.101-4, 5	Rel-15	pc_nr_enh_typeX_receiver	Support for Enhanced Type X Receiver
2	Vehicular UE	38.101-1, 3	Rel-15	pc_nr_vehicular_ue	

**Table A.4.3.9-2:** UE declared multi-band peak EIRP relaxation factors for FR2 power class 3

Item	Supported FR2 bands set	Ref.	Release	peak EIRP relaxation factor per band, $MB_p$ (dB) (Note 1)				Maximum sum of $MB_p$ , $\sum MB_p$ (dB) (Note 2)	Comments
				n257	n258	n260	n261		
1	n257, n258	38.101-2, 6.2.1.3	Rel-15			N/A	N/A	1.3	
2	n257, n260				N/A		N/A	1.0	
3	n258, n260			N/A			N/A	1.0	
4	n258, n261			N/A		N/A		1.0	
5	n260, n261			N/A	N/A	N/A	N/A	0.0	No relaxation factor allowed
6	n257, n258, n260						N/A	1.7	
7	n257, n258, n261					N/A		1.7	
8	n257, n260, n261				N/A			0.5	
9	n258, n260, n261			N/A				1.5	
10	n257, n258, n260, n261							1.7	

Note 1: UE vendor to fill in the needed relaxation factor per band that is  $\geq 0$ . One row to be filled in, the one matching the supported FR2 bands of the UE as declared in Table A.4.3.1-3.

Note 2: Max allowed sum of  $MB_p$  over all supported FR2 bands as defined in TS 38.521-2 clause 6.2.1.1.3.3

**Table A.4.3.9-3:** UE declared multi-band peak EIRP Spherical coverage relaxation factors for FR2 power class 3

Item	Supported FR2 bands set	Ref.	Release	EIRP Spherical coverage relaxation factor per band, $MB_s$ (dB) (Note 1)				Maximum sum of $MB_s$ , $\sum MB_s$ (dB) (Note 2)	Comments
				n257	n258	n260	n261		
1	n257, n258	38.101-2, 6.2.1.3	Rel-15			N/A	N/A	1.25	
2	n257, n260				N/A		N/A	0.75	Maximum 0.4 dB relaxation allowed for n260
3	n258, n260			N/A			N/A	0.75	Maximum 0.4 dB relaxation allowed for n260
4	n258, n261			N/A		N/A		1.25	
5	n260, n261			N/A	N/A			0.75	No relaxation allowed for n260
6	n257, n258, n260						N/A	1.75	Maximum 0.4 dB relaxation allowed for n260
7	n257, n258, n261					N/A		1.75	
8	n257, n260, n261				N/A			1.25	Maximum 0.4 dB relaxation allowed for n260
9	n258, n260, n261			N/A				1.25	Maximum 0.4 dB relaxation allowed for n260
10	n257, n258, n260, n261							1.75	Maximum 0.4 dB relaxation allowed for n260

Note 1: UE vendor to fill in the needed relaxation factor per band that is  $\geq 0$ . One row to be filled in, the one matching the supported FR2 bands of the UE as declared in Table A.4.3.1-3

Note 2: Max allowed sum of  $MB_s$  over all supported FR2 bands as defined in TS 38.521-2 clause 6.2.1.1.3.3

**Table A.4.3.9-4: 4 Rx antenna ports Capabilities**

Item	Ref.	Release	Band	Supported	Comments
1	38.101, 7.2	Rel-15	NR FDD Band 1		
2	38.101, 7.2	Rel-15	NR FDD Band 2		
3	38.101, 7.2	Rel-15	NR FDD Band 3		
...					
7	38.101, 7.2	Rel-15	NR FDD Band 7		Mandatory for non-vehicular UE if band support is indicated in Table A.4.3.1-1
...					
34	38.101, 7.2	Rel-15	NR TDD Band 34		
...					
38	38.101, 7.2	Rel-15	NR TDD Band 38		Mandatory for non-vehicular UE if band support is indicated in Table A.4.3.1-2
39	38.101, 7.2	Rel-15	NR TDD Band 39		
...					
40	38.101, 7.2	Rel-15	NR TDD Band 40		
41	38.101, 7.2	Rel-15	NR TDD Band 41		Mandatory for non-vehicular UE if band support is indicated in Table A.4.3.1-2
...					
48	38.101, 7.2	Rel-15	NR TDD Band 48		
...					
66	38.101, 7.2	Rel-15	NR FDD Band 66		
...					
70	38.101, 7.2	Rel-15	NR TDD Band 70		
...					
77	38.101, 7.2	Rel-15	NR TDD Band 77		Mandatory for non-vehicular UE if band support is indicated in Table A.4.3.1-2
78	38.101, 7.2	Rel-15	NR TDD Band 78		Mandatory for non-vehicular UE if band support is indicated in Table A.4.3.1-2
79	38.101, 7.2	Rel-15	NR TDD Band 79		Mandatory for non-vehicular UE if band support is indicated in Table A.4.3.1-2

## A.4.4 Additional information

**Table A.4.4-1: Additional information**

Item	Additional information	Ref.	Release	Mnemonic	Comments
1	Support of ICMP or ICMP IPv6	RFC 792 OR RFC 4443, RFC 4884	NA	pc_IP_Ping	UE supports ICMP or ICMPv6 protocol to enable IP Ping Operation
2	Support of IMS	24.229, Annex U	Rel-15	pc_IMS_5GS	

**Table A.4.4-2: Definition of UE implementation capabilities**

<b>Item</b>	<b>Definition of UE implementation capabilities</b>	<b>Ref.</b>	<b>Release</b>	<b>Mnemonic</b>	<b>Comments</b>
1	UE-requested PDU session establishment for IMS after REGISTRATION	24.501	Rel-15	pc_PDU_IMS	Configured to initiate PDU session establishment for IMS after REGISTRATION.
2	UE-requested PDU session establishment for Internet after REGISTRATION	24.501	Rel-15	pc_PDU_Internet	Configured to initiate PDU session establishment for Internet after REGISTRATION.
3	Number of UE-requested PDU session establishments after REGISTRATION	24.501	Rel-15	pc_noOf_PDUs	Number of UE-requested PDU session establishments after REGISTRATION.

## Annex B (informative): Change history

Change history							
Date	Meeting	TDoc	CR	R ev	Cat	Subject/Comment	New version
2017-12	RAN5#77	R5-176852	-	-	-	Introduction of TS 38.508-2	0.1.0
2018-04	RAN5#2- 5G-NR Adhoc	R5-182069	-	-	-	Addition of several required PICS	0.2.1
2018-05	RAN5#79	R5-183271	-	-	-	Addition of Missing PICS	1.0.0
2018-06	RAN#80	RP-181208	-	-	-	put under revision control as v15.0.0 with small editorial changes	15.0.0
2018-09	RAN#81	R5-185161	0001	1	F	Addition of PICS	15.1.0
2018-12	RAN#82	R5-187040	0010	-	F	Addition of new band into RF baseline implementation capabilities	15.2.0
2018-12	RAN#82	R5-187777	0011	1	F	Addition of PICS	15.2.0
2019-03	RAN#83	R5-192365	0020	1	F	Introduction of Physical Layer Baseline Implementation Capabilities for NR CA, NR DC and EN-DC	15.3.0
2019-03	RAN#83	R5-192706	0019	1	F	Introduction of Non 3GPP Access over WLAN PICS	15.3.0
2019-03	RAN#83	R5-192746	0017	1	F	Addition of Capability for test cases	15.3.0
2019-03	RAN#83	R5-192747	0018	1	F	PICS Update	15.3.0
2019-03	RAN#83	R5-192748	0021	1	F	Add UE capability PDU	15.3.0
2019-06	RAN#84	R5-193576	0027	-	F	Update of Clause 2 References of 38.508-2	15.4.0
2019-06	RAN#84	R5-193577	0028	-	F	Introduction of Table A.4.3.2A.2.1-3 configuration for FR1 Intra-band contiguous CA	15.4.0
2019-06	RAN#84	R5-193756	0030	-	F	Addition of UE capability for mobility	15.4.0
2019-06	RAN#84	R5-195137	0036	1	F	Addition of ICS for FR2 Multiband Relaxation declaration	15.4.0
2019-06	RAN#84	R5-195331	0031	1	F	PICS update	15.4.0
2019-06	RAN#84	R5-195428	0035	2	F	Resubmission: Addition of optional UE capabilities for Demod	15.4.0
2019-06	RAN#84	R5-195052	0029	1	F	Addition of CA_n41C CA_n66B and CA_n71B	16.0.0
2019-09	RAN#85	R5-197225	0037	1	F	Addition and Update of PICS	16.1.0
2019-09	RAN#85	R5-197440	0038	1	F	Addition of NR FR1 intraband non-contiguous and interband CA tables with combinations CA_66(2A), CA_n66A-n70A, CA_n66A-n71A, CA_n70A-n71A, CA_n66B-n70A, CA_n66(2A)-n70A, CA_n66(2A)-n71A to 38.508-2	16.1.0
2019-09	RAN#85	R5-197442	0045	-	F	Updates of SA and NSA information	16.1.0
2019-09	RAN#85	R5-197510	0044	1	F	Update to 38.508-2 for 4Rx handling	16.1.0